

# Connecting a Morley VandalProx to Net2

## Overview

The output from the Morley VandalProx reader is 26 bit Wiegand as standard.

The VandalProx uses the HID 125 kHz OEM module and therefore reads compatible HID tokens.

To configure the LED setting, open the Net2 server configuration utility and on the 'General' tab, check the 'Display reader LED's in OEM style' box.

If the option is not available, please contact Technical support for further advice.



Cable Pinout	ACU terminal
Red	+12V
-	Red LED
-	Amber LED
Orange	Green LED
Green	Wiegand D0
White	Wiegand D1
-	NOT USED
Black & Screen	0V

IO	Red 12V dc	Reader 1
IO	Red LED	
IO	Amber LED	
IO	Green LED	
IO	Data/D0	
IO	Clock/D1	
IO	Media Detect	
IO	0V out	

Ensure any unused wires are safely terminated.



+44 (0)1273 811011  
support@paxton.co.uk  
paxton.support



+49 (0) 251 2080 6900  
support@paxton-gmbh.de  
paxton.gmbh.support



+33 (0)157 329356  
support@paxtonaccess.fr  
paxton.support



+32 (0)78485147  
support@paxton-benelux.com  
paxton.benelux.support



+31 (0)76 3333 999  
support@paxton-benelux.com  
paxton.benelux.support



+27 (0)21 4276691  
support@paxtonaccess.co.za  
paxton.support



+1 (800) 672-7298  
supportUS@paxton-access.com  
usapaxton.support



+11 5715088198  
soporte@paxton-access.com  
paxton.soporte



+1 (864) 751-3501  
soporte@paxton-access.com  
paxton.soporte



8000 3570 3783  
support@paxtonaccess.ae  
paxton.support



+44 (0)1273 811011  
support@paxton.co.uk  
paxton.support