



How to configure system settings and backup

System settings

System options are only available to users with the software permissions set to 'Options'.

When configuring a system, there are a few settings that can be changed. To access these settings, select the 'System options' icon at the top right of the screen.



- Give the System a name (e.g. Paxton).
- Select the region that the system is in. This makes sure any daylight saving rules are applied correctly.
- Set the temperature units to be used within Paxton10.

Enable or disable remote access – allowing remote access provides users with a link to access the software outside of the company network.

- Set the length of PINs to be used for Keypads (4-8).
- Select the Reader Mode this should be set to Net2 if you have imported a CSV file containing token numbers from Net2
- Set the time either enter the time and date manually, or if connected to the internet choose to use internet time.
- Set the Date format to be used within Paxton10.

When finished amending the settings, click 'Save' to save and close the window.

Paxtor	10 Search Q		? 🍇 🛓 Charlotte Powell - 🔪 🔨			
DISTRICTOR	SUMMARY O Active users Total NOTIFICATION 46 Unacknowledged alarms Favourites EDII Create new Example alarms Favourites EDII Create new Example alarms Create new Example alarms Create new Example alarms Favourites EDII Favourites EDII Favourites EDII Favourites EDII Favou	OPTIONS X Custom days Custom fields Backup System Enail Data management About System setting: Integration of the construction o	27 Nov 28 Nov Today			

Backup the system

The System is backed up automatically each day, however it can also be backed up manually.

Manual backup

Select the 'System options' icon from the top right of the screen, select the 'Backup' tab, then select 'Backup now'

Paxto	n 10 Search Q	? 🍇 🔔 Charlotte Powell - 🔪 🔨			
	SUMMARY O 55 Active users Total NOTIFICATION 46 Unacknowledged alarms Office T Favourites EDIT	OPTIONS X Custom fields Backup System Enail Data management About Restore from backup Set date Loading Factory Reset Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its factory default. Default farefree Complete these two steps to restore your system to its facto	27 Nev ZB Nev Today		
DEVICES	Dashboard Event report Video report Site plan Per	Save Cancel			

The system can still be used while a backup is in progress. A notification message is displayed when the backup is complete.

Restore from backup

The system can be restored to a previous state. Restoring the system will restore all settings and elements to the state they were in when the system was backed up. All events and changes made since the chosen date will be lost.

- 1. Select the 'System options' icon from the top right of the screen, then select the 'Backup' tab
- 2. Select the date to restore from the drop down

3. Select 'Restore'

Paxtor	10 Search Q	? 🗞 🔝 Charlotte Powell ~ 🛛 🔨	
Control device	Add new		
		OPTIONS X	
HOME	SUMMARY	Custom days Custom fields Backup System Email Data management About Access events per day	
\bigcirc	0	- Backup	
DASHBOARDS	Active users Tot	Backup now	
		- Restore from backup	
<u>ר</u> ے	NOTIFICATION	Set date 29/11/2022 02:00:00 •	
SITE PLANS	46	27/11/2022 02:00:00 27/11/2022 02:00:00	
1	Unacknowledged alarms Offlin	Factory Reset 26/11/2022 02:00:00 25/11/2022 02:00:00 Complete these two the during the	27 Nov 29 Nov Today
PEOPLE		2/11/2022 02:00:01 22/11/2022 02:00:01 22/11/2022 02:00:00	
	Favourites EDII	21/11/2022 02:00:00 20/11/2022 02:00:00	
RULES		19/11/2022 2020:00 18/11/2022 02:00:00 12/11/2022 02:00:00	
	Create new	16/11/2022.02:00:00 15/11/2022.02:00:00	
DEVICES		14/11/2022.02:00:00 13/11/2022.02:00:00 13/11/2022.02:00:00	
		10/17/2022 02:00:00 10/17/2022 02:00:00	
	Uasnooaro Event report Video report Site plan F	son ime pronie autware autuary cuxomitule Device permission permission	

When the restore begins, all users will be logged out of the software. The Paxton10 software will redirect you to the login page when the restore is complete.

Return to system default

It is possible to factory reset the software to its default settings. Doing so will remove all user data and preferences, including any devices and bound system devices.

- 1. Select the 'System options' icon from the top right of the screen, then select the 'Backup' tab
- 2. Select **'Unbind Hardware'** This will unbind any hardware connected to allow it to be connected to a different system
- 3. Select 'Reset database' to factory reset the system

Paxton	? 🎕 🔝 Charlotte Powell - 🔪 🔨		
Control device	Add new		
НОМЕ	SUMMARY	OPTIONS X Orstom dark Crustom fields Backup System Email Data management About	
DASHBOARDS	0 5 Active users Total	Backup now	
	NOTIFICATION 46	Residre rom backup Set date 29/11/2022 02:00:00 Factory Reset	
		Complete these two steps to restore your system to its factory default.	27 Nov 28 Nov Today
	Favourites EDIT		
DEVICES			
	Dashboard Event report Video report Site plan Pe	son Time profile Software Building Custom rule Device	

All users will be logged out and the system restored with its initial settings. The Paxton10 software will redirect you to the first-time login page when the restore is complete, allowing you to create a new system engineer login.

Paxton 10 controllers bound to the system prior to the system restore may need to be reset before they can be redetected by the system. Hold down the reset button located on each controller for 10 seconds.