

Connecting a Remsdaq Entropad to Net2

Overview

The keypad reader was tested using a 32bit Custom Wiegand rule, using Net2 Software V6.04.9502.


Token data format (if custom Wiegand, include details of the required rule) Format tested was 32bit following custom Wiegand rule 'AA'.

Change the reader settings to Wiegand reader, and the token data format to Wiegand Custom. The keypad reader can be configured for both proximity and keypad input for use with Net2.

Note: Tokens will need to be enrolled via the reader to be used with Net2.



Cable Pinout	ACU terminal
Orange & White	+12V
Green	Red LED
-	Amber LED
Blue & white	Green LED
Blue	Wiegand D0
Green & White	Wiegand D1
-	NOT USED
Orange	0V



Ensure any unused wires are safely terminated.


For further information please visit manufacturers website: <https://www.remsdaq.com/solutions/integrated-security-systems/access-control-card-readers/entropad-card-readers/>


 +44 (0)1273 811011
 support@paxton.co.uk
 paxton.support


 +49 (0) 251 2080 6900
 support@paxton-gmbh.de
 paxton.gmbh.support


 +33 (0)157 329356
 support@paxtonaccess.fr
 paxton.support

 +32 (0)78485147
 support@paxton-benelux.com
 paxton.benelux.support


 +31 (0)76 3333 999
 support@paxton-benelux.com
 paxton.benelux.support

 +27 (0)21 4276691
 support@paxtonaccess.co.za
 paxton.support

 +1(800) 672-7298
 supportUS@paxton-access.com
 usapaxton.support

 +11 5715088198
 soporte@paxton-access.com
 paxton.soporte

 +1 (864) 751-3501
 soporte@paxton-access.com
 paxton.soporte

 8000 3570 3783
 support@paxtonaccess.ae
 paxton.support

 +44 (0)1273 811011
 support@paxton.co.uk
 paxton.support