

Connecting a Conlan Mifare M1200 to Net2

Overview

The unit tested was configured for 26 bit Wiegand output.


All three LEDs remain on and then when a valid card is presented, only the green LED flashes. The red flashes for access denied, the orange is on permanently in both cases.

The reader requires the ACU to control the LED's.

If the option is not available, please contact Technical support for further advice.



Cable Pinout	ACU terminal
Red	+12V
Orange	Red LED
-	Amber LED
Blue	Green LED
Green	Wiegand D0
White	Wiegand D1
Yellow and Brown	NOT USED
Black	0V



Ensure any unused wires are safely terminated.



+44 (0)1273 811011
support@paxton.co.uk
paxton.support



+49 (0) 251 2080 6900
support@paxton-gmbh.de
paxton.gmbh.support



+33 (0)157 329356
support@paxtonaccess.fr
paxton.support



+32 (0)78485147
support@paxton-benelux.com
paxton.benelux.support



+31 (0)76 3333 999
support@paxton-benelux.com
paxton.benelux.support



+27 (0)21 4276691
support@paxtonaccess.co.za
paxton.support



+1(800) 672-7298
supportUS@paxton-access.com
usapaxton.support



+11 5715088198
soporte@paxton-access.com
paxton.soporte



+1 (864) 751-3501
soporte@paxton-access.com
paxton.soporte



8000 3570 3783
support@paxtonaccess.ae
paxton.support



+44 (0)1273 811011
support@paxton.co.uk
paxton.support