



Entry

System specifications

Power over Ethernet (PoE)	Yes - IEEE 802.3af class 0
Ethernet bandwidth requirement	1Mb/s multicast per panel during call
Panels per system	100
Monitors per system	1000
TCP/IP ethernet extension limit	100m/328ft
Cable type	CAT5

Paxton Entry App Settings

App users	Up to 2,000 total app users (supports up to 6 devices per ID)*
Minimum Android version	Android 9.0
Minimum iOS version	iOS 15
Minimum Entry Config Version	v4.0
Video resolution displayed on mobile	640x480

Products available for Entry

- Entry - Panel
- Entry - VR Panel
- Entry - Monitor
- Entry - Control unit
- Entry - Extension switch
- Entry - Touch Panel
- Entry - Premium Monitor
- Entry - Audio Monitor
- Entry - Standard Monitor

Entry is a door entry system that works standalone or alongside Paxton's Net2 access control, combining door entry with key features of Net2 or as part of our access control and video management solution, Paxton10. Installing Entry is easy, as only one type of cable is needed between system components. Entry can be fitted using existing Cat5 infrastructure, and can connect to an existing IP network. The components, using IPV6, auto detect on setup, making installation straightforward with no specialist training required. Entry is a true plug and play solution; connect the components and the system works.

Entry comes in a discreet design that is suitable for a range of environments. The integral low light sensitivity camera works in day and night conditions, for extra security around the clock. The panel is IPX5 rated and will work in all weather conditions. An IK10 rated vandal resistant panel is also available. Constructed in 316 marine grade stainless steel with a toughened polycarbonate screen, this version is perfect for high-end sites and vandalism-prone areas.

Installation is flexible, with flush or surface mount options allowing you to take on a variety of jobs. Voice call, proximity and keypad capabilities mean your customers can mix and match to find what suits their needs. Integration with Net2 access control enables user access events at the Entry panel to be reported in Net2 software.

The Entry control unit contains a PoE switch, removing the need for local power. It also contains a backup battery option in the event of mains power failure. The system is easily scalable via a Entry extension switch or a third party PoE switch. This means you can offer Entry to customers at sites of any size. Using an extension switch allows expansion of up to a hundred panels and thousands of monitors.

Entry - Standard panel, surface mount	337-420-EX
Entry - Standard panel, flush mount	337-400-EX
Entry - Standard panel, surface mount with rain hood	337-410-EX
Entry - VR panel, surface mount	337-520-EX
Entry - VR panel, flush mount	337-500-EX
Entry - VR panel, surface mount with rain hood	337-510-EX
Entry - Control unit	337-727-EX
Entry - Extension switch	337-773-EX
Entry - Touch panel, surface mount	337-620-EX
Entry - Touch panel, flush mount	337-600-EX
Entry - Touch panel, surface mount with rainhood	337-610-EX
Entry - Premium monitor	337-290-EX
Entry - Premium monitor with handset	337-292-EX
Entry - Audio monitor	337-270-EX
Entry - Audio monitor with handset	337-272-EX
Entry - Standard monitor	337-280-EX
Entry - Standard monitor with handset	337-282-EX

Entry - Monitor desktop stand

337-294-EX



*The system supports a maximum of 2,000 total app users. Each ID (such as an apartment or tenant) can connect up to 6 individual users or devices, all of which will ring simultaneously. This does not increase the overall system capacity beyond the 2,000 user limit.